





## PRI58 SH / PRI58 H

## Features


- 58 mm case diameter
- · Hollow and semi-hollow shaft
- 100-200-360-400-500-600-720-1000-1024
   1800-2000-2048-2500-3600-4000-4096-5000 ppr.
- Push-Pull, TTL Linedriver and HTL Linedriver outputs
- Shaft diameter 6-8-10-12-14-15 mm 3500 rpm max.




## Technical Specifications

Resolution	100 to 5000 ppr.
Output Channels	A,B,Z or A, $\overline{A}$ , B, $\overline{\overline{B}}$ , Z, $\overline{\overline{Z}}$
Output type	Push-Pull, TTL Linedriver, HTL Linedriver
Supply voltage	5V DC or 8-24V DC or 5-24V DC
Power Comsumption	(without load) < 40 mA (24 VDC)
Cable	2.5m (Standard) 5 Wire+ Shield for Pushpull
	2.5m (Standard) 8 Wire + Shield for Linedriver
Max. Permissible Shaft Loading Radial Axial	


Max. Speed	3.500 rpm
Shaft Diameter	Ø6-8-10-12-14-15 mm
Shaft Material	Stainless Steel
Case Diameter	Ø58mm
Case Material	Aluminium and Painted Steel
IP degree	IP 54
Operating temperature	-20°C +80°C
Storage temperature	-30°C +90°C



SH Type (Radial)



H Type (Radial)



	SH (semi hollow)	/ H (hollow)
	С	D
DD1 50011 / 11	Ø6mm	20mm
PRI 50SH / H	Ø8mm	22mm
	Ø10mm	23,5mm
	Ø12mm	23,5mm
	Ø14mm	29,5mm
	Ø15mm	29,5mm

P	ush-F	'ull	Cable	Output

+V : Brown 0V : White GND : Shield Ch A : Yellow Ch B : Green Ch Z : Gray

Т	T	L	-	н	Т	L	Li	ne	dr	ΊV€	er (	Са	bl	е	o	ut	р	u

+V : Brown
0V : White
GND : Shield
Ch A : Yellow
Ch B : Green
Ch Z : Gray
Ch A inv.: Blue
Ch B inv.: Red
Ch Z inv.: Pink

Model	Case Diameter	Case Type	Shaft Diameter	Output Type	Resolution	Output Channels	Supply Voltage	Connector / Cable	Cable Output
(example) PRI	58	SH	8	HLD	1024	Z	V2	2M5	R
PRI	58mm	SH : Semi hollow H : Hollow	8 : 8mm	LTP: Push-pull TTL: TTL Linedriver HLD: HTL Linedriver		Z : A, B, Z B : A, B	V2:8-24V DC	2M5 : 2,5 meter cable 5M : 5 meter cable 8M : 8 meter cable 10M : 10 meter cable	R : Radial

Page 1/1

The information provided herein is to the best of our knowledge true and accurate, it is provided for guidance only. All specifications are subject to change without prior notification.